

# Pendleton SD

## Asterisk Phone Guide T43U

If you have any questions, please email in a Helpdesk ticket:  
[helpdesk.phone@imesd.k12.or.us](mailto:helpdesk.phone@imesd.k12.or.us)

### Basic Call Features

#### Placing a Call Using the handset:

1. Pick up the handset.
2. Enter the number, and then press the **Send** soft key.

#### Using the speakerphone:

1. With the handset on-hook,




press

2. Enter the number, and then press the **Send** soft key.



#### Using the headset:



1. With the headset connected, press  to activate the headset mode.
2. Enter the number, and then press the **Send** soft key.

**Note:** During a call, you can alternate between the headset, hands-free speakerphone and handset modes by pressing the **Headset** key, the **Speakerphone** key or by picking up the handset. Headset mode requires a connected headset.

#### Answering a Call

##### Using the handset:

Pick up the handset.

##### Using the speakerphone:



Press

##### Using the headset:



Press

**Note:** You can reject an incoming call by pressing the **Reject** soft key.


## Ending a Call

### Using the handset:

Hang up the handset or press the **End Call** soft key.

### Using the speakerphone:








Press  or the **End Call** soft key.

### Using the headset:

Press the **End Call** soft key.

## Redial

- Press  to enter the placed call list, press  or  to select the desired entry, and then press  or the **Send** soft key.
- Press  twice when the phone is idle to dial out the last dialed number.

## Call Mute and Un-mute



- Press  to mute the microphone during a call.
- Press  again to un-mute the call.

## Call Hold and Resume

### To place a call on hold:

Press the **Hold** soft key during an active call.

### To resume the call, do one of the following:

- If there is only one call on hold, press the **Resume** soft key.
- If there is more than one call on hold, press  or  to select the desired call, and then press the **Resume** soft key.

## Call Transfer

You can transfer a call in the following ways:

### Blind Transfer

1. Press the **Transfer** soft key during an active call. The call is placed on hold.
2. Enter the number you want to transfer to.
3. Press the **B Transfer** soft key.

### Semi-Attended Transfer

1. Press the **Transfer** soft key during an active call. The call is placed on hold.
2. Enter the number you want to transfer to, and then press the **Send** soft key.
3. Press the **Transfer** soft key when you hear the ring-back tone.



### Attended Transfer

1. Press the **Transfer** soft key during an active call. The call is placed on hold.
2. Enter the number you want to transfer to, and then press the **Send** soft key.
3. Press the **Transfer** soft key when the second party answers.

## Call Forward

To enable call forward:

1. Press the **Menu** soft key when the phone is idle, and then select **Features->Call Forward**.
2. Select the desired forward type:  
**Always Forward**----Incoming calls are forwarded unconditionally.  
**Busy Forward**----Incoming calls are forwarded when the phone is busy.  
**No Answer Forward**----Incoming calls are forwarded if not answered after a period of time.

3. Enter the number you want to forward to. For **No Answer Forward**, press  or  to select the desired ring time to wait before forwarding from the **After Ring Time** field.
4. Press the **Save** soft key to accept the change.

## Call Conference

1. Press the **Conference** soft key during an active call. The call is placed on hold.
2. Enter the number of the second party, and then press the **Send** soft key.
3. Press the **Conference** soft key again when the second party answers. All parties are now joined in the conference.
4. Press the **End Call** soft key to disconnect all parties.  
**Note:** You can split the conference call into two individual calls by pressing the **Split** soft key.

## Speed Dial

To configure a speed dial key:

1. Press the **Menu** soft key when the phone is idle, and then select **Features->Dsskey**.
2. Select the desired DSS key, and then press the **Enter** soft key.

3. Select **SpeedDial** from the **Type** field, select the desired line from the **Account ID** field, enter a label in the **Label** field and then enter the number in the **Value** field.
4. Press the **Save** soft key to accept the change.

#### To use the speed dial key:


Press the speed dial key to dial out the preset number.

#### Voice Message

Message waiting indicator on the idle screen indicates that one or more voice messages are waiting at the message center. The power indicator LED slowly flashes red.

#### To listen to voice messages:





1. Press  or the **Connect** soft key.
2. Follow the voice prompts to listen to your voice messages.

### Customizing Your Phone

#### Call History



Press the **History** soft key when the phone is idle, press  or  to scroll through the list.

1. Select an entry from the list, you can do the following:
  - Press the **Send** soft key to call the entry.
  - Press the **Delete** soft key to delete the entry from the list.

If you press the **Option** soft key, you can also do the following:

- Select **Detail** to view detailed information about the entry.
- Select **Add to Contacts** to add the entry to the local directory.
- Select **Add to Blacklist** to add the entry to the blacklist.
- Select **Delete All** to delete all entries from the list.


#### Contact Directory



##### To add a contact:

1. Press the **Directory** soft key when the phone is idle, and then select **All Contacts**.
2. Press the **Add** soft key to add a contact.
3. Enter a unique contact name in the **Name** field and contact numbers in the corresponding fields.
4. Press the **Add** soft key to accept the change.

##### To edit a contact:


1. Press the **Directory** soft key when the phone is idle, and then select **All Contacts**.





2. Press  or  to select the desired contact, press the **Option** soft key and then select **Detail** from the prompt list.
3. Edit the contact information.
4. Press the **Save** soft key to accept the change.

#### To delete a contact:


1. Press the **Directory** soft key when the phone is idle, and then select **All Contacts**.



2. Press  or  to select the desired contact, press the **Option** soft key and then select **Delete** from the prompt list.
3. Press the **OK** soft key when the LCD screen prompts "Delete selected item?".  
**Note:** You can add contacts from call history easily. For more information, refer to **Call History** above.

#### Volume Adjustment




- Press  during a call to adjust the receiver volume of the handset/speakerphone/headset.



- Press  when the phone is idle or ringing to adjust the ringer volume.





- Press  to adjust the media volume in the corresponding screen.



#### Ring Tones

1. Press the **Menu** soft key when the phone is idle, and then select **Settings->Basic Settings->Sound-> Ring Tones**.



2. Press  or  to select **Common** or the desired account and then press the Enter soft key.



3. Press  or  to select the desired ring tone.
4. Press the **Save** soft key to accept the change.